

Antennenkoppler aus Baumarktmaterial (Cu-Rohr nach DIN EN1057)

Außenrohr (Cu)	Typ	18x0,8	22x1	22x0,9	28x1	28x1,5	35x1	35x1,5
	Innenmaß (mm)	16,6	20	20,2	26	25	33	32
Innenleiter (Cu)	8mm*		54,9Ω	55,5Ω				
	10mm*	30,4Ω	41,6Ω	42,2Ω		54,9Ω		
	12mm	19,5Ω	30,7Ω	31,3Ω	46,4Ω	44,0Ω		
	15mm				33,0Ω	30,7Ω	47,3Ω	45,4Ω
	18mm				22,1Ω	19,7Ω	36,4Ω	34,5Ω
	22mm						24,3Ω	22,5Ω

* Messing, nur
bedingt geeignet

Soll-Impedanz	25Ω
	28,9Ω
	35,4Ω
	50Ω