Importieren der digitalen user Datenbank in das Anytone AT-D868UV oder AT-D878UV

1. man lädt sich die neueste user-Datenbank hier: https://ham-digital.org/status/ herunter:

Https://ham-digital.org/status/							
🞆 register.ham-digital.org	Downloads	×					
👍 Z Beim Zimbra-Webclient a	🍪 www.funkboerse	🏧 FA-Kleinanzeigen	📧 Amateurfunk eBay Kleina	SP StartPage by I			

Downloads

All data provided here are only for non commercial Amateur Rac

This download page provides actual data of registered DMR users and repeaters for Amateur Radio DM DSTAR lists are for completeness to be used with DSTAR-DMR-Gateways and cross-network reflector Lists are updated automatically every 6 hours.

Any commercial use of data which are provided from this server is strictly prohibited!

Data protection / data usage regulations

DMR User ID List in CVS format (ID;call;)	
DMR User ID List, space separated fields (ID call name)	
OMR User IDs in 'Digital Contact List' format of Anytone D868 (all IDs world	lwide, zipped) 📃

2. wenn man die .zip Datei dekomprimiert hat, importiert man die .csv Datei mit diesen Einstellungen in ein Tabellenkalkulations Programm, z.B. "open office":

mportiere	n							ОК
Z <u>e</u> ichen	satz	Westeuropa	(Windows-1	252/WinLati	n 1) 🔻	\mathbf{N}		
Spra <u>c</u> he	prache Standard - Deutsch (Deutschland)							Abbrechen
Ab <u>Z</u> eile		1 🌲						<u>H</u> ilfe
Trennoptio	onen							
© <u>F</u> este	Breite							
() Getre	ennt							
<u> </u>	abulator	<u>Ko</u>	nma	<u>A</u> n	dere			
<u>S</u> e	mikolon	🔳 Lee	rzeichen					
E Fe	ldtrenner zusa	mmenfasser		Texttren	er		-	
E Fe	l <u>d</u> trenner zusa	mmenfasser	I.	Te <u>x</u> ttrenr	ier	"	•	
E Fe 💭 Weitere Op	el <u>d</u> trenner zusa	mmenfasser		Te <u>x</u> ttrenr	ier	"	•	
Veitere Op	e in H <u>o</u> chkom	mmenfasser ma als Text	•	Te <u>x</u> ttrenr	ier	н	-	
Veitere Op Weitere Op Wert	el <u>d</u> trenner zusa otionen e in H <u>o</u> chkom iterte Zahlener	mmenfasser ma als Text kenn <u>u</u> ng	•	Te <u>x</u> ttrenr	ner	н	•	
Veitere Op Weitere Op Wert	el <u>d</u> trenner zusa otionen e in H <u>o</u> chkom iterte Zahlener	mmenfasser ma als Text kenn <u>u</u> ng	•	Te <u>x</u> ttrenr	ier	"	•	
Veitere Op Weitere Op Wert Erwei Felder	l <u>d</u> trenner zusa otionen e in H <u>o</u> chkom iterte Zahlener	mmenfasser ma als Text kenn <u>u</u> ng	•	Te <u>x</u> ttrenr	ner	H	•	
Felder Spaltent	el <u>d</u> trenner zusa otionen e in H <u>o</u> chkom iterte Zahlener	mmenfasser ma als Text kenn <u>u</u> ng		Te <u>x</u> ttrenr	ier	H	•	
Feitere Op Werte Erwe Feider Spaltent	el <u>d</u> trenner zusa ptionen e in H <u>o</u> chkom iterte Zahlener ¥P ndard Standar	mmenfasser ma als Text kenn <u>u</u> ng d Standar		Te <u>x</u> ttrenr	Standard	"		
Weitere Op Weitere Op Wert Erwei Felder Spaltent Spaltent	e in H <u>o</u> chkom iterte Zahlener YP Radio	mmenfasser ma als Text kenn <u>u</u> ng d Standar ID Callsig	J Standard yn Name	Te <u>x</u> ttrenr Standard City	Standard State	" Standard Country		
Felder Spaltent	e in H <u>o</u> chkom iterte Zahlener YP Radio 202100	mmenfasser ma als Text kennung d Standard ID Callsig	J Standard Jn Name SV1BYK	Texttrenr Standard City Babis	Standard State	" Standard Country Greece		
Veitere Op Wertere Op Wertere Erwei Spaltent No. 2 1 3 2	e in Hochkom iterte Zahlener WP Radio 202100 202100	mmenfasser ma als Text kenn <u>u</u> ng d <u>Standar</u> ID Callaig 1	J Standard Jn Name SV1BYK SV1PDW	Texttrenr Standard City Babis Ioannis	Standard State	" Standard Country Greece Greece		
Felder Spaltent Star 1 No. 2 1 3 2 4 3	e in Hochkom iterte Zahlener yp ndard Standar Radio 202100 202100 202100	mmenfasser ma als Text kenn <u>u</u> ng d Standar ID Callaid 1 2 3	J Standard Jn Name SV1BYK SV1EDW SV1IW	Texttrenr Standard City Babis Icannis Manos	Standard State	" Standard Country Greece Greece Greece		
Feeder Spaltent	e in Hochkom iterte Zahlener XP ndard Standar Radio 202100 202100 202100 202100	mmenfasser ma als Text kenn <u>u</u> ng d Standard ID Callaig 1 2 3 4	J Standard Jn Name SV1BYK SV1PDW SV1EQI	Texttrenr Standard City Babis Ioannis Manos Dimitris	Standard State	" Standard Country Greece Greece Greece Greece		
Feder Spaltent	e in Hochkom iterte Zahlener xp idard Standar 202100 202100 202100 202100 202100	mmenfasser ma als Text kennung d Standard ID Callsid 1 2 3 4 5	SV1PW SV1PW SV1PU SV1EQI SV1DAR	Texttrenr Standard City Babis Icannis Manos Dimitris Antonis	Standard State	" Standard Country Greece Greece Greece Greece		
Felder Spaltent Stan 1 No. 2 1 3 2 4 3 5 4 6 5 7 6	e in Hochkom iterte Zahlener XP Radio 202100 202100 202100 202100 202100 202100 202100 202100	mmenfasser ma als Text kennung d Standar ID Callsig 1 2 3 4 5 5 6	Standard Jn Name SV1BYK SV1PDW SV1IW SV1EQI SV1DAR SV1GFH	Texttrenr Standard City Babis Ioannis Manos Dimitris Antonis Andreas	Standard State	" Standard Country Greece Greece Greece Greece Greece Greece		

3. Die nun generierte Tabelle enthält unter den Überschriften in den Spalten leider nicht die dazugehörigen Daten. Das muss jetzt umsortiert werden:

53											
🛅 anyt	one_digital	contact_lis	t.csv - OpenOffic	e Calc	Service in the	read to find out in	wheel a burner long			- market -	
<u>D</u> atei	<u>B</u> earbeiten	<u>A</u> nsicht	<u>E</u> infügen <u>F</u> orm	at E <u>x</u> tras Da <u>t</u>	en Fen <u>s</u> ter <u>H</u> ilfe						
1	2 •	🗠 📝) 🗟 🖴 🕵	ABS ABS	🖺 🛍 • 🛷 崎 • (@ - 🚳 🔂 👪 [🛓 🖉 i 👬 🧭 💼 🗟	9	Finden	- 4	Ŷ.
9	Arial		• 10 •	F <i>K</i> <u>∪</u>	E Ξ ∃ ■ 🖽	📕 % 💱 號 👯	∉ 🍕 🗆 • 🖄 • 🔺	-			
A2:AN	IJ2		∑ = 1								
	Α	В	С	D	E	F	G	Н	I	J	K
1	No.	Radio ID	Callsign	Name (City	State	Country	Remarks	Call Type	Call Alert	
92099	92098	3154231	Mt. Hope	K8GDG	Gary	West Virginia	United States		Private Call	None	
92100	92099	3154232	Ravenswo	NAVV	Samuel S	West Virginia	United States		Private Call	None	
92101	92100	3154233	Morganto	KE8DCG	Blaine	West Virginia	United States		Private Call	None	
92102	92101	3154234	Morganto	KE8DCG	Blaine	West Virginia	United States		Private Call	None	
92103	92102	3154235	Bridgepo	KE8HYU	Troy	West Virginia	United States		Private Call	None	
92104	92103	3154236	Elkins /	AB8E	Maurice G	West Virginia	United States		Private Call	None	
92105	92104	3154237	Moundsvi	WD8BXS	Carl A	West Virginia	United States		Private Call	None	
92106	92105	3154238	Parkersb	N8KNA	Richard R	West Virginia	United States		Private Call	None	
92107	92106	3154239	Morganto	W8CUL	West Virginia U	West Virginia	United States		Private Call	None	
92108	92107	3154240	Point PI	AB8S	Gail E	West Virginia	United States		Private Call	None	
92109	92108	3154241	Huntingt	KD80IF	Jonathan	West Virginia	United States		Private Call	None	
92110	92109	3154242	Buckhann	KC8JDC	Jonathan S	West Virginia	United States		Private Call	None	

4. Da es für mich in open office calc einfacher ist ganze Spalten zu verschieben als gut 100.000 Daten unter den Überschriften zu markieren und unter die richtige Überschrift zu bewegen ändere ich zuerst nur die Überschriften (C1, D1und E1) um im nächsten Schritt die Reihenfolge der ganzen Spalten richtig zu stellen:

1	anytone_digital_contact_list_download.csv - OpenOffice Calc										
Dat	<u>D</u> atei <u>B</u> earbeiten <u>A</u> nsicht <u>E</u> infügen <u>F</u> ormat E <u>x</u> tras Da <u>t</u> en Fen <u>s</u> ter <u>H</u> ilfe										
: 5											
: •		_ @	-		v 🗠 🗖		S I S Z♥ A♥ I L				
. 9	Ĩ® Arial I0 F K U Ξ Ξ ≡ I ♣ % 🐉 號 💥 ∉ 🤕 □ • Ѯ • ♣ • 🖕										
E92	2103		▼ 3%	∑ = Dway	/ne A						
	-	Α	B	C	D	E	F	G	Н	I	J
	1	No.	Radio ID	City	Callsign	Name	State	Country	Remarks	Call Type	Call Alert
92	2099	92098	3153796	Brush Pr	ABIF	John N	Washington	United States		Private Call	None
92	2100	92099	3153797	Stattle	WOVIY	St. phen M	Washington	United States		Private Call	None
92	2101	92100	3153798	Vancouve	KI7SHJ	Lawrence W	Washington	United States		Private Call	None
92	2102	92101	3153799	Port Tow	KE4CNU	Harry C	Washington	United States		Private Call	None
92	103	92102	3153800	Olympia	KI7QZD	Dwayne A	Washington	United States		Private Call	None
92	2104	92103	3153801	Port Ang	W7NRO	Richard T	Washington	United States		Private Call	None
92	2105	92104	3153802	Bellevue	K9LUP	Thomas	Washington	United States		Private Call	None
92	2106	92105	3153803	Airway H	KG7ZCW	Daniel B	Washington	United States		Private Call	None
92	2107	92106	3153804	Renton	K7RFH	Richard F	Washington	United States		Private Call	None
92	2108	92107	3153805	Oroville	KI7AAV	Wayne W	Washington	United States		Private Call	None
92	2109	92108	3153806	Port Orc	W7PLW	Patrick L	Washington	United States		Private Call	None
92	2110	92109	3153807	Cashmere	N7RHT	Larry D	Washington	United States		Private Call	None
0.2	1111	02110	2462000	loogguph		Harmann	Washington	United States		Drivete Cell	Mana

5. Ich füge zwischen den Spalten B und C eine neue ,leere Spalte ein und ändere dann die Reihenfolge der Spalten C, D und E mit "cut" und "paste" und lösche die dann leere Spalte G. Die Tabelle muss jetzt genau so aussehen (Wenn ihr das auf einem anderen Weg hinbekommt, nur zu. Das Ergebnis zählt!):

	F1		▼ <i>f</i> ×	📡 = Sta	te						
		Α	B	C	D	E	F	G	Н	I	J
I	1	No.	Radio ID	Callsign	Name	City	State	Country	Remarks	Call Type	Call Alert
I	92099	92098	3153796	AB7F	John N	Brush Pr	Washington	United States		Private Call	None
I	92100	92099	3153797	W0TTY	Stephen M	Seattle	Washington	United States		Private Call	None
I	92101	92100	3153798	KI7SHJ	Lawrence W	Vancouve	Washington	United States		Private Call	None
I	92102	92101	3153799	KE4CNU	Harry C	Port Tow	Washington	United States		Private Call	None
I	92103	92102	3153800	KI7QZD	Dwayne A	Olympia	Washington	United States		Private Call	None
I	92104	92103	3153801	W7NRO	Richard T	Port Ang	Washington	United States		Private Call	None
I	92105	92104	3153802	K9LUP	Thomas	Bellevue	Washington	United States		Private Call	None
I	92106	92105	3153803	KG7ZCW	Daniel B	Airway H	Washington	United States		Private Call	None
I	92107	92106	3153804	K7RFH	Richard F	Renton	Washington	United States		Private Call	None
I	92108	92107	3153805	KI7AAV	Wayne W	Oroville	Washington	United States		Private Call	None
I	92109	92108	3153806	W7PLW	Patrick L	Port Orc	Washington	United States		Private Call	None
I	92110	92109	3153807	N7RHT	Larry D	Cashmere	Washington	United States		Private Call	None
1	0.0444	00110	2452000		Llauran	la a a su cala	10/ him at a m	United Chatra		Deiverte Cell	Mana

6. Jetzt kann man die Datei im .csv Format abspeichern (dabei muss unbedingt das Kästchen "Filtereinstellungen bearbeiten" aktiviert sein):

B Speichern unter	High line ips light high lith							
COO V Eigene Do	kume 🕨 anytone_digital_contact_list 🔹 👻	← anytone_digital_contact_list d						
Organisieren 🔻 Neuer	Ordner	ii 🗸 🔞						
 ✓ Favoriten E Desktop Downloads Zuletzt besucht Ziletzt besucht Bibliotheken E Bilder E Dokumente Musik Videos 	Bibliothek "Dokumente" anytone_digital_contact_list Name 1 anytone_digital_contact_list	Anordnen nach: Ordner 🔻 Änderungsdatum 31.12.2018 21:05						
🖻 剩 Heimnetzgruppe	 ✓ 	•						
Dateiname: anyto	ne_digital_contact_list	•						
Dateityp: Text C	SV (.csv)	•						
Dateityp: Text CSV (.csv) ✓ Automatische Dateinamenserweiteru ng Mit Kennwort mit Kennwort mit Kennwort mit Kennwort prichem Filtereinstellungen bearbeiten								
Ordner ausblenden		Speichern Abbrechen						

7. Filtereinstellungen genau so vornehmen:

Exportiere Text Datei	Producted Name	23
Feldoptionen		OK
<u>Z</u> eichensatz	Westeuropa (Windows-1252/WinLatin	
<u>F</u> eldtrenner		<u>A</u> bbrechen
Texttrenner		<u>H</u> ilfe
🔽 <u>A</u> lle Textze	llen zitieren	
Zellinhalt wie	angezeigt	
Feste Spalten	preite	

8. Wenn man alles richtig gemacht hat, muss die Dateivorschau im Windows-Explorer genau so aussehen (sehr wichtig sind die Anführungszeichen):

	"No."."Radio ID"."Callsign"."Name"."City"."State"."Country"."Remarks"."Call Type"."Call Alert"
Biblio	"1","2021001","5v1BYK","Babis",,,"Greece",,"Private Call","None"
Anoranen nach: Oraner •	"2","2021002","SV1PDW","Ioannis",,,"Greece",,"Private Call","None"
anytone	"3","2021003","SV1IW","Manos",,,"Greece",,"Private Call","None"
*	"4","2021004","SV1EQI","Dimitris",,,"Greece",,"Private Call","None"
Name	"5","2021005","SV1DAR","Antonis",,,"Greece",,"Private Call","None"
	"6","2021006","SV1GFH","Andreas",,,"Greece",,"Private Call","None"
anytone_digital_contact_list	"7","2021007","SV1LJG","Stelios",,,"Greece",,"Private Call","None"
	"8","2021008","SV1UY","Dimitrios",,,"Greece",,"Private Call","None"
anytone_digital_contact_list_download	"9","2021009","SV1NJT","Athanasios",,,"Greece",,"Private Call","None"
	"10","2021010","SV1FKQ","Dimitrios",,,"Greece",,"Private Call","None"
	"11","2021011","SV1EDZ","DIMITRIS",,,"Greece",,"Private Call","None"
	"12" "2021012" "SV1AW " "Panagiotis" "Greece" "Private Call" "None"

9. Zum Vergleich die Vorschau der heruntergeladenen Datei:

Biblio Anordnen nach: Ordner -	"No.", "Radio ID", "Callsign", "Name", "City", "State", "Country", "Remarks", "Call Type", "Call Alert" "1", "2021001", "", "SVIBYK", "Babis", ", "Greece", "", "Private Call", "None" "2", "2021002", "", "SVIBYK", "Dannis", "", "Greece", "", "Private Call", "None" "3", "2021003", "", "SVIIW", "Manos", "", "Greece", "", "Private Call", "None"
Name	"4","2021004","","SVIEQI","Dimitris","","Greece","","Private Call","None" "5","2021005","","SVIDAR","Antonis","","Greece","","Private Call","None" "6" "2021006" "" "SVIEEH" "Andreas" "" "Greece","" "Private Call","None"
anytone_digital_contact_list	77", "2021000", ", "Svluh", "Andreas", ", "Greece", ", "Private Call", "None"
anytone_digital_contact_list_download	"9","2021008, ",","SVINY, DIMITTOS, ", Greece", "Private Call, None"
	"10","2021010","","SV1FKQ","Dimitrios","","Greece","","Private Call","None" "11","2021011","","SV1EDZ","DIMITRIS","","Greece","","Private Call","None"

10. jetzt kann man die digitale user Datenbank im csv-Editor importieren:

D878UV[D878UV:UHF{430 - 440	MHz} VH	IF{144 - 146 MH	lz}][:C:\Users\sl	olmin	wents\Anutone\codenlug_20	10-01-02 rdt1		~
e Model Set Program (To	ol) View	Help	\rightarrow	🔛 Imp	ort			~
ት 🚘 🔲 🕫 🕺 👘 👘	0.0							
7811		Receive	Transmit				Import From File List	
Public	No.	Frequency	Frequency		Channel			=
Channel	1	439.56250	431.96250		Channel			_
Zone	2	439.56250	431.96250		Radio ID List			
- Scan List	3	439.56250	431.96250		7			-
Roaming Zone	4	439.56250	431.96250		Zone]		_
FM	5	439.56250	431.96250		Scan List			
Auto Repeater Offset Frequer	6	439.56250	431.96250			1		-
Roaming Channel	7	439.56250	431.96250		Analog Address Book	ļ		_
Basic information	8	439.56250	431.96250		Talk Groups			_
···· Optional Setting	9	439.56250	431.96250					-
- Alarm Setting	10	438.92500	431.32500		Digital Contact List	C:\Users\sholm\Documents\Anytone	\anytone_digital_contact_list\anytone_digital_contact_list1.CSV	_
- Local Information	11	438.92500	431.32500		Prefabricated SMS			_
Hot Key	12	438.92000	431.32000	-		1		- 1
APRS	13	438.92000	431.32000		FM			
Digital	14	430.92300	431.32300		Receive Group Call List		1	
Analog	10	430.33000	430.33000	_]		_
	10	145.00230	145.00230		5Tone Encode			
	18	/38 55000	/30.95000		Tono Excede			-
	19	438,85000	431 25000		210fie Encode			_
	20	438 95000	431 19000		DTMF Encode			
	21	439 15000	431 55000	_	11.47 0 1 0 1			- 1
	22	439.05000	431,45000		Hotkey_QuickCall]		_
	23	145.77500	145.17500		HotKey_State			
	24	/138 25000	//30.65000					-
F]	•				HotKey_HotKey			_
878UV					Auto Repeater Offset Frequencys			
port Window	and the Second	6		-		1		_
lick on j import from file Listj± to i lick on j import + to I and the select	Load the information	tion from the cor	e corresponding responding CSV		Roaming Channel][_
now on 1 importing to coad the select		Non non late out	coponally .000		Roaming Zone		/	_
nis feature allow importing from an ex	cel spread	dsheet each of th	e programming f		-	1		
itus						Import		

viel Erfolg mit der Anleitung wünscht DB7SH